

Prepared by:	Date Prepared:
Anna Litzkow	January 10, 2018

Tools Needed

• (1) Blank 1GB+ USB Flash Drive

Matrix Fitness software updates

- Desktop or Laptop Computer
- Internet Connection

Performing Update

1. Firmly plug your Flash Drive into your computer's USB port. Ensure the Flash Drive does not have any other files on it.

Note: It is helpful to know the 'name' of your Flash Drive, as we will need to locate this drive in a later step. In this example, the drive is named "FLASH DRIVE (E:)".

- From your web browser, visit <u>https://www.horizonfitness.com/support/software-updates</u> and locate the section featuring software for your brand of machine: Horizon, Vision, Matrix, or Livestrong. (For AFG products, software is located at <u>http://www.afgfitness.com/support/software-update</u>.)
- **3.** Locate your unit or console type under "Model", and then click the link under "Software" to initiate the software download.

Model	Software
XR Consoles	v8.001
XER/XIR Consoles	v1.2.17.0

4. The download will say that it has (x) seconds left until complete. Once the download is complete, click the symbol next to where it says "zip", then select "Show in folder".

XR Consoles	Open
XER/XIR Consoles	Always open files of this type
Livestrong software u	Show in folder
Ū.	Cancel
xr-v8-001.zip	~

This will open your computer's Downloads folder, where you will see a zipped folder.



5. Click the folder to highlight it, and then right-click the folder to open the drop-down menu; select "Extract All..."



6. Click "Browse..."

Select a Destination and Extract Files



Show extracted files when complete

7. On the left side of the window, locate your Flash Disk (remember the name from Step 1); click it to highlight it, and then click "Select Folder".

1 Select a destination					×
\leftarrow \rightarrow \checkmark \Uparrow This PC \Rightarrow FLASH DISK (E:)		ٽ ~	Search FLASH	DISK (E:)	P
Organize 🔻 New folder				-	?
 Desktop Documents Downloads Music Pictures Videos Local Disk (C:) Coal Disk (C:) Ctoal Disk (E:) cts department (X:) group share (Z:) FLASH DISK (E:) Network 	Date modified No items match yo	Type ur search.	Size		
Folder: FLASH DISK (E:)			Select Folder	Cancel	



8. Select "Extract".

4

ion and Extract Files to this folder: Browse	Extract Co	mpressed (Zipped)	Folders		
to this folder: Browse	Select a De	estination and	Extract Files		
Browse	Files will be e	tracted to this fold	ler:		
	E:\				Browse
s when complete	E:∖ ☑ Show extra	octed files when co	mplete		Browse

Extract Cancel

 Once the extraction is complete, the contents of the zipped folder will appear on the next screen. <u>Do not make any changes to these files</u>; simply right-click your Flash Drive and select "Eject" to safely remove it from your computer.

Matrix XER/XIR (Touch Screen) Consoles:

- From the home/GO screen on your XER/XIR console, tap the gear in the top-right corner, then tap 'Machine Settings'. (*Do NOT plug your Flash Drive into the console's USB port until Step 12.*)
- **11.** On the left-hand side of the screen that appears, tap 'Update'.
- **12.** Firmly plug your Flash Drive into the console's USB port.
- 13. Tap 'Update from USB'.

All Other Units and Consoles:

- **10.** With your console powered on, firmly plug your Flash Drive into the console's USB port (See the Owner's Manual if you are unsure of the location of this port.)
- **11.** Monitor your console throughout the software update. Some consoles will automatically begin the update as soon as the Flash Drive is inserted, however others may require some user input.

Note: If your console states "no updates found" after you have inserted the Flash Drive, this indicates that your software version was current prior to attempting the update. No further action is required.